

IPC/PTZ/NVR upgrade on web 5

Tiandy Technical Support Team 23/08/2020

Description

IPC/PTZ/NVR upgrade on web5

Prerequisites

- Already got FW

Set up steps

1. Choose English here then enter the user name/password and login.



The screenshot shows the Tiandy web interface. At the top left is the Tiandy logo. At the top right is a language selection dropdown menu with 'English' selected and highlighted by a red box. Below the logo, there are three input fields: 'User Name' with 'admin' entered, 'Password' (empty), and 'Port' with '3000' entered. A green 'Login' button is positioned below the input fields.

2. Select 'Configuration'.

The screenshot shows the Tiandy web interface with the 'Configuration' menu highlighted in red. The main content area displays the 'Stream Set' configuration page. On the left, a sidebar menu lists various settings: Stream Set, Camera Set, OSD, Network Management, User Management, Alarm Management, and Advance Set. The 'Stream Set' configuration includes a dropdown for 'Stream' (1st Stream), a 'General Set' section with fields for Resolution (1080P(1920x1080)), Bit Rate (4096), Frame Rate (25), N/P Mode (PAL), Priority (Frame Rate), Video Quality (Good), I-Frame Interval (50), and Encoding Mode (Variable Bit Rate). At the bottom, there is a 'Smooth Video Streaming' slider set to 50, with a label '[Clarity<->Smooth]'.

3. Choose 'Advance Set'-'System Maintenance'.

The screenshot shows the Tiandy web interface with the 'System Maintenance' option in the sidebar highlighted with a red box. The main content area displays the 'System Maintenance' page. It is divided into three sections: 'Device Control' with buttons for 'Basic Recovery', 'Comple..ecovery', 'Reboot', and 'Open re..service'; 'Configuration In/Out' with an 'Import' field (format: (*.box)), a 'Browse' button, and an 'Import' button, and an 'Export' button; and 'Firmware Upgrade' with an 'Upgrade File' field (format: (*.bin)or(*.box)), a 'Browse' button, and an 'Upgrade' button.

4. Find 'Firmware Upgrade' and click 'Browse' to choose the upgrade box we send you.

The screenshot shows the Tiandy web interface with the 'Configuration' tab selected. The left sidebar contains a menu with 'System Maintenance' highlighted. The main content area is titled 'System Maintenance' and includes sections for 'Device Control' (with buttons for Basic Recovery, Complet...covery, Reboot, and Open re...service), 'Configuration In/Out' (with fields for Import and Export), and 'Firmware Upgrade' (with a file selection field and an 'Upgrade' button). The 'Firmware Upgrade' link and the 'Browse' button are highlighted with red boxes.

5. Click 'Upgrade' to finish S3E/S6 upgrade on web5. Do not turn off the power during upgrading.